

# **Technical Data** VEXU-24C

Digital Color Matrix Camera, 2.3 Megapixel, USB 3.0 Article No. 11151568 Firmware Revision 1.0














Model Name	Sony IMX249
Туре	1/1.2" progressive scan CMOS
Shutter	Global Shutter
Resolution	1920 x 1200 pixels
Scan Area	11.25 mm x 7.03 mm
Pixel Size	5.86 µm x 5.86 µm




Data Quality	@ 20 °C, gain = 1, exposure time = 4 msec
Dark Noise (σ)	7.9 e- typical
Saturation	32000 e- typical
Dynamic Range	71 dB typical
SNR	45 dB typical
Quantum efficiency η	57 % @ 465 nm, 62 % @ 536 nm, 47 % @ 631 nm typical

#### Acquisition

- 10 0 0 110 110 11			
Resolution	1920 px x 1200 px	(	
Acquisition Frame Rate	38 fps   $t_{readout} = 25$	5.8 msec (max. Res. Fu	Il Frame) @ 12 bit1)
Interface Frame Rate	Format	Resolution	max. Frame Rate (@ Trigger Mode)
(depends on used USB interface	Full Frame	1920 x 600	38 fps
performance)	Binning 2x2	960 x 600	38 fps
	Binning 2x1	960 x 1200	38 fps
	Binning 1x2	1920 x 600	38 fps
Pixel Formats	BayerRG8, Bayer	RG12	
Partial Scan		with increasing Fran	




direction, Region of Interest (ROI) arbitrary Width: minimum 16, increment 16 Heigth: minimum 4, increment 4 Adjustable Acquisition Off or Off or 0.01 ... 1200 Hz



Frame Rate	
Acquisition Mode	Continuous, Single Frame and Multi Frame
Acquisition Status	AcquisitionActive, AcquisitionTrigger Wait
Exposure Mode	Timed

#### Image Pre-Processing


Analog Controls	Gain (048 dB), Offset (0 255 LSB   12 bit)
Color Models	Raw Bayer
Binning Horizontal	1 or 2
Binning Vertical	1 or 2
Image Flipping	no
Defect Pixel Correction	via Defect Pixel List with up to 512 Pixel Coordinates



### **Process Synchronization**

Trigger Mode	Off (Free Running), On (Trigger)
Trigger Overlap Type	Readout
Trigger Sources	Hardware (Line0), Software or Off fixed Trigger Delay out of treadout: 1) 46 µsec @ 12 bit max. Trigger Delay during treadout: 1) 62.5 µsec @ 12 bit
Trigger Delay	-
External Flash Sync	via Exposure Active
	$t_{delay flash} \le 3 \mu sec, t_{duration} = t_{exposure}$

<sup>1)</sup> Sensor readout, different from pixel format






Lines	Input: Line 0, Output: Line1
Output Sources	Off, ExposureActive
Line Debouncer	Low and high signal separately selectable
	Debouncing Time 0 5 msec, Step Size: 1 µsec

Memory

Image Buffer	no image buffer
	no image buffer (Trigger Mode) / no (Free Running Mode)
Non-volatile Memory	128 kb



#### Interface Data

Interface	USB3.0 (5000 Mbits/sec)
USB Vendor ID / Product ID	0x2825 / 0x127

## USB 3 Vision® Features

Events	•
Transmission via Asynchronous	
Message Channel	
Frame Counter	up to 2 <sup>32</sup>
Payload Size	0 4608000 Byte
Timestamp	64 bit
USB Vision	v1.0.1

#### Interfaces and Connectors

interraces ar	nterfaces and connectors				
Data and Power	USB 3.0 USB 2.0	Transfer Rate 5000	Mbits/sec		
Interface	Connector:	USB 3.0 Micro B			
	Pin Assignment:	VBUS	MicB_SSTX-		
		D-	MicB_SSTX+		
		D+	GND_DRAIN		
		ID	MicB_SSRX-		
		GND	MicB_SSRX+		
Process	Connector:	M8/4-pin (SACC-DSI-M 8	BMS-4CON-L180)		
Interface	Assignment:	1 - VCC (Out)	3 - GND (IN)		
		2 - IN+	4 - OUT		

Caution \* Note I/Os: Ground loops are to be avoided and can lead to destruction of the device.




#### **Optical Data**

Lens Mount	CS-Mount	
Optical Filter	IR cut filter	


#### **Mechanical Data**

Housing	Zinc die casting, nickel-chrome-plated,
	IP40 (with mounted lens and USB 3.0 cable)





Weight	90 g



#### **Environmental Data**

Storage Temperature	-10 °C + 70 °C
Operating Temperature *)	+5 °C +65 °C @ T = Measurement Point Ambient temperature above 50 °C requires heat dissipation measures
Humidity	10 % 90 % non-condensing

<sup>&</sup>quot;) the maximum temperature for Sony sensor characteristics (sensor performance) are guaranteed up to "C @ Measurement Point

**LED Signalling** 

LED	Green flash	Power on, no link active
	Green	Link active USB 3.0
	Red	Error
	Yellow	Sensor Readout activity
	Red flash	Update


#### Pin Assignment Process Interface (on camera side)



wire colors on connecting cables (ordered separately)		
1 Brown	2 White	


Blue Black

# Device Temperature: T = Measurement





# LED Signalling



#### **Electrical Data**

Power Supply (ext.) bus powered via USB3.0 interface **Power Consumption** 1.5 W @ 38 fps (Factory Setting "Default") direct, without optocoupler **Digital Input**  $U_{\text{IN(low)}}$ : 0.0 ... 0.8 VDC  $U_{IN(high)}$ : 3.3 ... 30 VDC <10 mA I<sub>IN</sub>: min. Impulse Length: 2.0 µsec Digital Output

direct, without optocoupler  $U_{\text{EXT}}$ : 5...30 V DC max. 50 mA I<sub>OUT</sub>:

 $t_{\rm ON}$  = typ. 1.5 µsec  $t_{\rm OFF}$  = typ. 40 µsec \* The digital I/Os are not potential-free and do not have an overrun cut-off.  $t_{ON} = typ. 1.5 \mu sec$ 

Caution Incorrect wiring (overvoltage, undervoltage or voltage reversal) can lead to defects in the electronic system.

Ground loops are to be avoided and can lead to destruction of the device.

#### Conformity

Conformity	CE, RoHS, REACH
KC Registration No. / Date	- / -
MTBF	-/-
	T = Measurement Point

## GenlCam<sup>™</sup> Features

Timer	-	
User Sets	Factory Settings: Freely Programmable: Parameters:	UserSet0 (read only) UserSet1 any user definable Parameter
Acquisition Abort	Delay up to 25.77 msec	
SFNC Version	v2.1	

#### antom, Cattinga after Start IIn

Factory Settings after Start-Up		
Trigger Mode	Off (Free Running)	
Analog Controls	Exposure Time: 4 msec, Gain: 0 dB, Offset: 0	
Pixel Format	BayerRG8	
Partial Scan	Off	
Acquisition Frame Rate	-	
Timer	-	
Defect Pixel Correction	ON	
Fixed Pattern Noise	-	
Correction		
Digital Input	Line0, invert = false	
Digital Output	Line1, invert = false, line source = Off	
GPIO 1/2	-	
TriggerSource	Off	

Partial Scan @ FullFrame, min Exposure, Mono8 or BayerRG8

esolution	max. fps acquisition	max. fps interface 2)
1920 x 1080	42	43
1280 x 1024	45	45
1024 x 768	59	59
800 x 600	75	75
640 x 480	92	92
352 x 288	147	147
176 x 144	263	263
1920 x 1024	45	45
1920 x 512	87	87
1920 x 256	163	163
1920 x 128	289	289
1920 x 64	470	470
1920 x 32	685	685
1920 x 16	888	887
1920 x 8	1043	4041
1920 x 4	1142	1138
1920 x 2	1200	1996
1920 x 1		-
	1280 x 1024 1024 x 768 800 x 600 640 x 480 352 x 288 176 x 144 1920 x 1024 1920 x 512 1920 x 256 1920 x 128 1920 x 64 1920 x 32 1920 x 16 1920 x 8 1920 x 4 1920 x 2	1920 x 1080

<sup>2)</sup> depends on the used interface