IR12.P06S-F40.PC1Z.7BCV

Inductive proximity switch - large sensing distance

Article number: 11148657

Overview

- 6 mm
- PNP break function (NC)
- cable, 2 m
- -25 ... 75 °C
- IP 67



Picture similar





Technical data	
General data	
Mounting type	Flush
Special type	Enhanced distance (GammaProx)
Nominal sensing distance Sn	6 mm
Temperature drift	± 10 %
Hysteresis	3 20 % of Sr
Output indicator	LED red
Correction factor typ.	Mild steel 100 %, stainless steel 75 %, aluminum 45 %
Electrical data	
Switching frequency	1 kHz
Voltage supply range +Vs	6 36 VDC
Current consumption max. (no load)	10 mA
Output circuit	PNP break function (NC)

Electrical data	
Voltage drop Vd	< 2 VDC
Output current	< 100 mA
Short circuit protection	Yes
Reverse polarity protection	Yes
Mechanical data	
Туре	Cylindrical threaded
Material (sensing face)	PBT
Housing material	Brass nickel plated
Dimension	12 mm
Housing length	40 mm
Connection types	Cable, L=2 m
Tightening torque max.	15 Nm (A: 10 Nm)
Ambient conditions	
Operating temperature	-25 +75 °C
Protection class	IP 67

Remarks

Triple sensing distance




IR12.P06S-F40.PC1Z.7BCV


Inductive proximity switch - large sensing distance

Article number: 11148657


Dimension drawing




Connection diagram



Correction factors for different mounting situation (approx.)



Mounting material	Correction factor
Mild steel	100 %
Stainless steel	100 %
Aluminum	100 %



Mounting material	Correction factor
Mild steel	100 %
Stainless steel	95 %
Aluminum	95 %



Mounting material	Correction factor
Mild steel	not possible
Stainless steel	95 %
Aluminum	80 %



IR12.P06S-F40.PC1Z.7BCV

Inductive proximity switch - large sensing distance

Article number: 11148657

Mounting instructions

