# IR18.D08L-Q60.IA1E.7BO

Inductive distance sensors - linearized

Article number: 11164789

### Overview

- 0 ... 8 mm
- current output
- external Teach-in
- connector M12
- -25 ... 75 °C
- IP 67



Picture similar





Technical data	
General data	
Mounting type	Quasi-flush
Special type	Linearized
Measuring distance Sd	0 8 mm
Sensitivity	2,0 mA/mm
Resolution	< 0.002 mm (stat.) < 0.006 mm (dynam.)
Repeat accuracy	0.015 mm
Adjustment	External Teach-in
Teach	1-point analog, 2-point analog, factory reset
Linearity error	± 32 μm
Temperature drift	± 4 % (Full Scale)
Teach-Feedback	LED yellow
Electrical data	
Response time (factory characteristic)	< 1 ms
Voltage supply range +Vs	12 36 VDC
Current consumption max. (no load)	20 mA

Electrical data	
Output circuit	Current output
Output signal	4 20 mA
Load resistance	< 50 Ohm/V * Vs - 250 Ohm > 500 Ohm (Vs = 30 36 VDC)
Short circuit protection	Yes
Reverse polarity protection	Yes
Mechanical data	
Design	Cylindrical threaded
Material (sensing face)	PBT
Housing material	Brass nickel plated
Dimension	18 mm
Housing length	60 mm
Connection types	Connector M12
Tightening torque max.	40 Nm
Ambient conditions	
Operating temperature	-25 +75 °C
Protection class	IP 67


### Remarks

- External Teach-in
- Linear analog output


# IR18.D08L-Q60.IA1E.7BO

Inductive distance sensors - linearized Article number: 11164789

### **Dimension drawing**



## **Connection diagram**



### Pin assignment

