

Through hollow shaft, optical multiturn encoders 13 bit ST / 12 bit MT, SSI

Article number: 11246065

#### Overview

- Absolute encoder multiturn
- Optical sensing method
- Resolution: singleturn 13 bit, multiturn 12 bit
- Maximum resistant against magnetic fields
- Connection: flange connector M23, 12-pin, CCW



atings
830 VDC
Yes
Yes
≤80 mA (24 VDC)
SSI
Multiturn
8192 / 13 bit
4096 / 12 bit
±0.03 °
Optical
Gray
CW: ascending values with clockwise sense of rotation; looking at flange
SSI clock Zero setting input Counting direction
SSI data: Linedriver RS422
SSI data
EN 61000-6-2
EN 61000-6-4

Technical data - electrical r	atings	
Approval	UL-Listing: E217823	
Technical data - mechanical design		
Size (flange)	ø58 mm	
Shaft type	ø14 mm (through hollow shaft)	
Protection EN 60529	IP 54 (flange side) IP 65 (housing side)	
Operating speed	≤6000 rpm (+25 °C)	
Starting torque	≤0.04 Nm	
Motor shaft tolerance	± 0.2 mm (axial offset) ≤ 0.1 mm (radial offset) ≤ 0.1 mm (concentricity)	
Material	Housing: aluminium Shaft: stainless steel	
Operating temperature	-25+85 °C (see general information)	
Relative humidity	95 % non-condensing	
Resistance	IEC 60068-2-6 Vibration ±0.75 mm - 10-58 Hz, 10 g - 58- 2000 Hz EN 60068-2-27 Shock 100 g, 11 ms	
Weight approx.	400 g	
Connection	Flange connector M23, 12-pin, CCW	

Through hollow shaft, optical multiturn encoders 13 bit ST / 12 bit MT, SSI

Article number: 11246065

#### **General information**

Terminal assignment

Self-heating correlated to installation and ambient conditions as well as to electronics and supply voltage must be considered for precise thermal dimensioning. Operating the encoder close to the maximum limits requires measuring the real prevailing temperature at the encoder flange.

Terrinia ass	Terminal assignment	
Flange socket M23, 12-pin, male contact, CCW		
Pin	Assignment	
1	Data-	
2	-	
3	SET	
4	DIR	
5	Clock+	
6	Clock-	
7	-	
8	Data+	
9	-	
10	0 V	
11	-	
12	+Vs	


1 9 8
10 12 7
\\\\3 • 0 •6 \\\\\
\\\\ 4●11●5 ////

Terminal significance		
SET	Zero setting input. Input for zero setting at any position. The zero setting operation is triggered by a high pulse and has to be in line with the selected direction of rotation (DIR). Impulse duration >100 ms. Connect to 0 V after zero setting for maximum interference immunity.	
DIR	Counting direction input.  This input is standard on high.  DIR-High means ascending output data with clockwise shaft rotation when looking at flange.  DIR-Low means ascending values with counterclockwise shaft rotation when looking at flange.  For maximum interference immunity connect to +Vs respectively 0 V depending on counting direction.	

Trigger level	
SSI	Circuit
SSI-Clock	RS422 with terminating resistor 120 Ω
SSI-Data	RS422

Control inputs	Input circuit	
Input level High	>0.7 UB	
Input level Low	<0.3 UB	
Input resistance	10 kΩ	

#### Data transfer




Clock frequency f	802000 kHz
Delay time tv	70 ns (RL = 120 Ohm)
Monoflop time tm	16 24 μs + T/2
Clock interval tp	30 µs


2023-11-09





Through hollow shaft, optical multiturn encoders 13 bit ST / 12 bit MT, SSI Article number: 11246065

#### **Dimensions**









Through hollow shaft, flange socket M23



Through hollow shaft, optical multiturn encoders 13 bit ST / 12 bit MT, SSI Article number: 11246065

Accessories		
Mounting accessories		
11066083	Torque arm, 1-arm (mounting kit 006)	
11073119	Torque arm, 1-arm (mounting kit 021)	
11067367	Torque arm, 1-arm (mounting kit 028)	
11100198	Stator coupling, 2-armed (mounting kit 046)	
11113210	Torque arm, 1-arm (mounting kit 047)	
11124300	Torque arm, 1-arm (mounting kit 048)	
11106627	Fan cover clip 8 mm	
11116921	Insulating sleeve ø10 mm/ø12 mm/25 mm long	
11116923	Insulating sleeve ø12 mm/ø14 mm/25 mm long	